A New Outer Bound for the Discrete Memoryless Two-User Interference Channel

Amin Gohari
Dept. of Information Engineering
The Chinese University of Hong Kong
Hong Kong, China
agohari@ie.cuhk.edu.hk

Chandra Nair
Dept. of Information Engineering
The Chinese University of Hong Kong
Hong Kong, China
cnair@ie.cuhk.edu.hk

Jinpei Zhao
Dept. of Information Engineering
The Chinese University of Hong Kong
Hong Kong, China
zj022@ie.cuhk.edu.hk

Abstract

We establish a new outer bound on the capacity region of the discrete memoryless two-user interference channel via a pair of auxiliary receivers. Our approach unifies and extends several previously known outer bounds for discrete memoryless interference channels. For the Gaussian interference channel with weak interference, we show that the new outer bound passes through both Costa–Polyanskiy–Wu corner points and the maximum sum-rate point, and exhibits all three known slope discontinuities of the true capacity region in this regime.

Index Terms

Interference channels, Gaussian interference channel, outer bounds, sum-capacity, slope discontinuity.

I. Introduction

A. Interference channel

In this paper, we consider the two-sender, two-receiver interference channel $T_{Y_1,Y_2|X_1,X_2}$ illustrated in Figure 1. Each sender wishes to transmit a message to its respective receiver over a shared medium, modeling communication in two nearby cells of a wireless system.

Standard notions such as message sets, encoding and decoding functions, average probability of error, and achievable regions are defined in the usual way. For an overview of interference channels, see [1, Chap. 6].




Fig. 1. Two-sender, two-receiver interference channel.

As shown in Figure 1, the interference channel is modeled by the transition probability $T_{Y_1,Y_2|X_1,X_2}(y_1,y_2|x_1,x_2)$. A widely studied instance is the (scalar real) Gaussian interference channel, given by

$$Y_1 = X_1 + bX_2 + Z_1, \qquad Y_2 = X_2 + aX_1 + Z_2,$$

where X_1 and X_2 are subject to average power constraints P_1 and P_2, respectively, $a, b \in [0,\infty)$ are interference gains, Z_1 and Z_2 are standard Gaussian noise variables, and Y_1 and Y_2 are the received signals. A Gaussian interference channel is therefore specified by the four parameters (a, b, P_1, P_2). We say that the interference channel is a Gaussian Z-interference channel if either $a = 0$ or $b = 0$, so that receiver 1 or receiver 2 experiences no interference from the other sender.

The *sum-capacity* is defined by

$$C(T) := \sup_{(R_1,R_2)\in\mathscr{C}} (R_1 + R_2),$$

where $\mathscr{C}$ denotes the capacity region. For a Gaussian interference channel with parameters (a, b, P_1, P_2), the sum-capacity $C(T)$ is known in the following parameter regimes:

(i) $a, b \geq 1$, corresponding to strong interference, where the entire capacity region is characterized in [2], [3].
(ii) $a \geq 1, b < 1$ or $a < 1, b \geq 1$, where the capacity region is characterized in [2].
(iii) $a(1+b^2P_2)+b(1+a^2P_1) < 1$ (very weak interference), where the sum-capacity was independently established in [4]–[6].

In the remainder of this paper, when considering Gaussian interference channels, we restrict attention to the weak interference regime $a, b < 1$.




Fig. 2. Gaussian interference channel.

B. Background on outer bounds for Gaussian interference channels

Several outer bounds have been developed for Gaussian interference channels in the weak interference regime. A first class of bounds arises from genie-aided constructions, in which carefully designed side information is provided to the receivers; a general form of such a weighted sum-rate bound is given in [7, Th. 2.1.1]. For the Gaussian interference channel, Liu and Nair's weighted sum-rate outer bound leads to sharp characterizations of $\sup_{(R_1,R_2)\in\mathcal{C}}(\lambda R_1 + R_2)$ for a range of slopes $\lambda \geq 1$ when $a(1+b^2P_2)+b(1+a^2P_1) \leq 1$ [7], [8]. In particular, when λ lies in an explicit interval, the optimal weighted sum-rate is achieved by treating interference as noise at both receivers, and the resulting expression coincides with the sum-capacity.

Genie-aided outer bounds are special cases of a broader family known as auxiliary-receiver bounds. Auxiliary receivers are abstract analytical constructs introduced to investigate capacity regions in communication networks. They do not exist in the original physical model and act as passive observers that neither transmit information nor decode messages. Such receivers have been widely used in network information theory, including studies of the relay channel, the broadcast channel, and the interference channel (see, for example, [9]–[13]).

When auxiliary receivers are designed as enhanced versions of the actual receivers, the resulting bounds specialize to genie-aided bounds. Nevertheless, auxiliary receivers that are not of the genie type can be highly effective. In these scenarios, the "add-and-subtract" technique naturally arises as a method for deriving outer bounds, and several bounds based on this idea have been developed. Notably, for Gaussian Z-interference channels, an outer bound derived using the add-and-subtract approach is presented in [11]. There, an auxiliary receiver J is introduced, together with a factorization of the joint law of (J, Y_1, Y_2) that enforces rate constraints on R_1 and R_2 for some choice of auxiliary random variables. In the Gaussian Z-interference case, this leads to an outer bound that is tight near the corner points of the capacity region and, in particular, yields a second slope discontinuity at a Costa–Polyanskiy–Wu corner point that is not captured by previously known genie-aided bounds.

Although these two approaches pinpoint different segments of the capacity boundary, none of the existing outer regions captures all three slope discontinuities of the true capacity region of the Gaussian interference channel in the weak interference regime within a single unified bound. The genie-aided bound from [7], [8] is active near the maximum sum-rate point, whereas the auxiliary-receiver bound of [11] is active near the Costa–Polyanskiy–Wu corner points. This motivates the construction of a combined outer bound that simultaneously retains the strengths of both techniques. The new bound incorporates both add-and-subtract and genie-based manipulations in a single outer region.

II. Some previously known outer bounds

A. Genie-aided outer bounds

We first recall the general genie-aided outer bound for discrete memoryless interference channels formulated in [7, Th. 2.1.1].

Theorem 1 (Genie-aided bound)**.** *Consider an interference channel $T_{Y_1,Y_2|X_1,X_2}$ and auxiliary receivers G, K with joint distribution*

$$p(y_1, y_2, g, k|x_1, x_2) = p(g|x_1)\, p(k|x_2)\, p(y_1, y_2|g, k, x_1, x_2),$$

such that the marginal $p(y_1, y_2|x_1, x_2)$ coincides with the original channel. Then, for any $\lambda \geq 0$,

$$\begin{aligned}\sup_{(R_1,R_2)\in\mathcal{C}} (R_1 + \lambda R_2) \leq \sup_{p(x_1)p(x_2)} \Big(& I(X_1; G, Y_1) + \lambda I(X_2; K, Y_2) \\ & + \mathcal{C}_{p(x_1)p(x_2)}[I(X_1; G|X_2, K) - \lambda I(X_1; Y_2|X_2, K)] \\ & - (I(X_1; G|X_2, K) - \lambda I(X_1; Y_2|X_2, K)) \\ & + \mathcal{C}_{p(x_1)p(x_2)}[I(X_2; K|X_1, G) - I(X_2; Y_1|X_1, G)] \\ & - (I(X_2; K|X_1, G) - I(X_2; Y_1|X_1, G)) \Big),\end{aligned}$$

where $\mathcal{C}$ denotes the capacity region and $\mathcal{C}_{p(x_1)p(x_2)}[\cdot]$ is the upper concave envelope evaluated over product input distributions.

For Gaussian interference channels in the weak interference regime, a specialization of this bound yields the following result [8, Th. 3.4].

Theorem 2 (Weighted sum-rate outer bound [7], [8])**.** *Consider a Gaussian interference channel with parameters (a, b, P_1, P_2) satisfying $a(1 + b^2P_2) + b(1 + a^2P_1) \le 1$. For any $\lambda \ge 1$ such that*

$$\lambda \le 1 + \frac{(1 - a(1 + b^2P_2))^2 - b^2(1 + a^2P_1)^2}{b^2\big((1 + a^2P_1)^2 + P_2(1 - a(1 + b^2P_2))\big)},$$

it holds that

$$\sup_{(R_1,R_2)\in\mathcal{C}} (\lambda R_1 + R_2) = \frac{\lambda}{2}\log\left(1 + \frac{P_1}{1 + b^2P_2}\right) + \frac{1}{2}\log\left(1 + \frac{P_2}{1 + a^2P_1}\right),$$

where $\mathcal{C}$ is the capacity region.

Thus, in a neighborhood of the maximum sum-rate point, the optimal strategy is to treat interference as noise, and the resulting weighted sum-rate exhibits a slope discontinuity at the sum-capacity point.

B. Auxiliary-receiver bound for Z-interference channels

Consider a general Z-interference channel

$$T_{Y_1,Y_2|X_1,X_2} = T_{Y_1|X_1} T_{Y_2|X_1,X_2},$$

so that receiver 1 experiences no interference from X_2. The authors in [11] derived an outer bound with one auxiliary receiver using the add-and-subtract manipulation:

Theorem 3 (Corollary 2 in [11])**.** *Let J be defined by a channel $T_{J|X_1,X_2,Y_1,Y_2}$ such that*

$$p_{J,Y_1,Y_2|X_1,X_2} = T_{Y_1,Y_2|X_1,X_2}\, T_{J|X_1,X_2,Y_1,Y_2}$$

and

$$p_{J,Y_1,Y_2|X_1,X_2} = p_{J|X_1}\, p_{Y_2|J,X_2}\, p_{Y_1|J,X_1},$$

with J more-capable than Y_1. Then any achievable rate pair (R_1, R_2) must satisfy

$$\begin{aligned} R_1 &\le \min\{I(X_1; Y_1|Q),\ I(W; Y_2|Q) + I(X_1; J|W, Q)\},\\ R_2 &\le \min\{I(X_2; Y_2|W, X_1, Q),\ I(X_2; Y_2|W, Q) - I(X_2; J|W, Q)\}, \end{aligned}$$

for some $p(q)p(x_1|q)p(x_2|q)p(w|x_1, x_2, q)$ such that

$$I(X_1; J|W, Q) \ge I(X_1; Y_2|W, Q).$$

In the Gaussian Z-interference case, this leads to the following weighted sum-rate characterization [11, Th. 4]. Let $\mathcal{R}_{\mathrm{OB}}$ denote the outer region of a certain Gaussian Z-interference channel, $C_2 = \frac{1}{2}\log(1 + P_2)$, and $R_1^* = \frac{1}{2}\log\big(1 + \frac{a^2P_1}{1+P_2}\big)$. Then, for all slopes λ above a certain threshold depending on a and P_2, one has

$$\max_{(R_1,R_2)\in\mathcal{R}_{\mathrm{OB}}} \lambda R_2 + R_1 = \lambda C_2 + R_1^*.$$

Theorem 4 (Theorem 4 in [11])**.** *Let $\mathcal{R}_{\mathrm{OB}}$ denote the outer bound given in Theorem 3. Let $C_2 = \frac{1}{2}\log(1 + P_2)$ and $R_1^* = \frac{1}{2}\log\Big(1 + \frac{a^2P_1}{1+P_2}\Big)$. Then*

$$\max_{(R_1,R_2)\in\mathcal{R}_{\mathrm{OB}}} \lambda R_2 + R_1 = \lambda C_2 + R_1^*$$

whenever

$$\lambda \ge 1 + \begin{cases} \dfrac{(1 + P_2)(1 - a^2)}{a^2P_2}\,\dfrac{\left(1 + \sqrt{1 + 4a^2(1 - a^2)P_2}\right)^2}{4a^2(1 - a^2)P_2}, & a^2 < \frac{1}{2},\\ \dfrac{(1 + P_2)(1 - a^2)}{a^2P_2}\,\dfrac{\left(1 + \sqrt{1 + P_2}\right)^2}{P_2}, & a^2 \ge \frac{1}{2}. \end{cases}$$

This shows that the auxiliary-receiver bound is tight near a Costa–Polyanskiy–Wu corner point and yields another slope discontinuity in the capacity boundary, complementary to the one provided by the genie-aided bound near the sum-rate point.




Fig. 3. Sketch of the capacity region of the Gaussian interference channel when $a, b > 0$ and $a(1+b^2P_2)+b(1+a^2P_1) \le 1$, showing slope discontinuities at three points.

C. Motivation for a unified bound

Combining these two approaches shows that, in the weak interference regime, the capacity region of the Gaussian interference channel has at least three points of slope discontinuity: one at the maximum sum-rate point and two at the Costa–Polyanskiy–Wu corner points. However, the existing outer bounds only capture subsets of these discontinuities. The genie-aided bound matches the boundary near the sum-rate point, while the auxiliary-receiver bound (based on the add-and-subtract manipulation) is tight near the corner points. Our goal is to construct a single outer bound that simultaneously exhibits all three slope discontinuities and interpolates between these regimes.

III. A New Outer Bound

We now introduce a combined outer bound that incorporates both genie-aided and add-and-subtract techniques. Consider an arbitrary interference channel $T_{Y_1,Y_2|X_1,X_2}$ and auxiliary receivers G, K with joint distribution

$$p(y_1, y_2, g, k|x_1, x_2) = p(g|x_1)\, p(k|x_2)\, p(y_1, y_2|g, k, x_1, x_2), \tag{1}$$

such that the marginal $p(y_1, y_2|x_1, x_2)$ coincides with the original channel.

In addition, we require the following less-noisy-type inequalities to hold for all joint laws p_{X_1,X_2} and all auxiliary variables U, V:

$$I(U; Y_1|X_1) \le I(U; K|X_1), \qquad \forall\, U \to (X_1, X_2) \to (Y_1, K), \tag{2}$$
$$I(V; Y_2|X_2) \le I(V; G|X_2), \qquad \forall\, V \to (X_1, X_2) \to (Y_2, G). \tag{3}$$

Under these structural assumptions, we obtain the following single-letter outer bound.

Theorem 5 (Combined interference channel bound)**.** *Let $T_{Y_1,Y_2|X_1,X_2}$ be an arbitrary interference channel, and let (G, K) be auxiliary receivers satisfying* (1) *and the less-noisy-type conditions* (2)–(3)*. Then any achievable rate pair (R_1, R_2) in the capacity region must satisfy*

$$\begin{aligned} R_1 &\le I(X_1; Y_1|X_2, W_3, Q) - I(X_1; G|X_2, W_3, Q) \\ &\quad + I(X_1; G|W_2, Q) + I(W_2; Y_2|Q), \end{aligned} \tag{4}$$
$$R_1 \le I(X_1; Y_1|X_2, W_1, Q), \tag{5}$$
$$R_1 \le I(X_1; Y_1|W_1, Q) - I(X_1; K|W_1, Q), \tag{6}$$
$$R_1 \le I(V_1, W_1, X_1; Y_1|Q), \tag{7}$$

and

$$\begin{aligned} R_2 &\le I(X_2;Y_2|X_1,W_4,Q) - I(X_2;K|X_1,W_4,Q) \\ &\quad + I(X_2;K|W_1,Q) + I(W_1;Y_1|Q), \qquad (8) \\ R_2 &\le I(X_2;Y_2|X_1,W_2,Q), \qquad (9) \\ R_2 &\le I(X_2;Y_2|W_2,Q) - I(X_2;G|W_2,Q), \qquad (10) \\ R_2 &\le I(V_2,W_2,X_2;Y_2|Q). \qquad (11) \end{aligned}$$

Moreover, the sum-rate is bounded by

$$\begin{aligned} R_1+R_2 \le\ & I(X_1,X_2;Y_1|G,Q) + I(X_1,X_2;Y_2|K,Q) \\ & + I(X_2;K|V_1,W_1,X_1,G,Q) - I(X_2;Y_1|V_1,W_1,X_1,G,Q) \\ & + I(X_1;G|V_2,W_2,X_2,K,Q) - I(X_1;Y_2|V_2,W_2,X_2,K,Q), \qquad (12) \end{aligned}$$

where the joint distribution of the auxiliary random variables factorizes as

$$p(q)p(x_1|q)p(x_2|q)p(w_1,v_1|x_1,x_2,q)p(w_2,v_2|x_1,x_2,q)p(w_3|x_1,x_2,q)p(w_4|x_1,x_2,q)$$

and satisfies the constraints

$$\begin{aligned} & I(X_1;Y_1|X_2,W_3,Q) - I(X_1;G|X_2,W_3,Q) \\ & \quad + I(X_1;G|W_2,Q) - I(X_1;Y_2|W_2,Q) \ge 0, \qquad (13) \\ & I(X_2;Y_2|X_1,W_4,Q) - I(X_2;K|X_1,W_4,Q) \\ & \quad + I(X_2;K|W_1,Q) - I(X_2;Y_1|W_1,Q) \ge 0. \qquad (14) \end{aligned}$$

Remark 1. Bounds on the cardinalities of the auxiliary random variables can be obtained through a standard application of Carathéodory's theorem.

A. Proof of the combined outer bound

In this section we prove Theorem 5. We start from an arbitrary (n,ϵ) code for the interference channel, introduce the auxiliary receivers (G^n,K^n), and then single-letterize the resulting multi-letter expressions using suitably chosen auxiliary random variables. Throughout, δ_n and δ_n' denote nonnegative quantities that go to zero as $n\to\infty$ and $\epsilon\to 0$.

1) Code-induced joint distribution and auxiliary receivers: Fix an (n,ϵ) code with message sets $\mathcal{M}_1=\{1,\dots,2^{nR_1}\}$ and $\mathcal{M}_2=\{1,\dots,2^{nR_2}\}$, encoding functions, and decoding functions for the two users. This induces a joint distribution on

$$(M_1,M_2,X_1^n,X_2^n,Y_1^n,Y_2^n),$$

where the message pair (M_1,M_2) is uniformly distributed and independent, and the codewords $X_1^n(M_1)$ and $X_2^n(M_2)$ are independent. The channel is memoryless, so

$$T_{Y_1^n,Y_2^n|X_1^n,X_2^n}(y_1^n,y_2^n|x_1^n,x_2^n)=\prod_{i=1}^n T_{Y_1,Y_2|X_1,X_2}(y_{1i},y_{2i}|x_{1i},x_{2i}).$$

Now define auxiliary sequences G^n,K^n through the memoryless channel

$$T_{G^n,K^n|X_1^n,X_2^n,Y_1^n,Y_2^n,M_1,M_2}=\prod_{i=1}^n T_{G_i,K_i|X_{1i},X_{2i},Y_{1i},Y_{2i}},$$

which, by assumption, satisfies (1). Thus the effective channel from (X_1^n,X_2^n) to (G^n,K^n) is memoryless and factorizes as $T_{G^n|X_1^n}T_{K^n|X_2^n}$.

We assume the less-noisy-type conditions (2)–(3) for all input distributions p_{X_1,X_2}.

2) Single-letter auxiliaries and time sharing: For $i \in \{1,\dots,n\}$ and a sequence $x^n = (x_1,\dots,x_n)$, we write $x^{n\setminus i}$ for the $(n-1)$-tuple obtained by removing x_i. To single-letterize, we introduce a time-sharing random variable Q uniformly distributed over $\{1,\dots,n\}$, independent of all other variables. For each time index $i \in \{1,\dots,n\}$, define

$$\begin{aligned} V_{1i} &= (X_1^{n\setminus i}, G^{n\setminus i}), & V_{2i} &= (X_2^{n\setminus i}, K^{n\setminus i}),\\ W_{1i} &= (K^{i-1}, Y_{1,i+1}^n), & W_{2i} &= (G^{i-1}, Y_{2,i+1}^n),\\ W_{3i} &= (X_2^{n\setminus i}, Y_1^{i-1}, G_{i+1}^n), & W_{4i} &= (X_1^{n\setminus i}, Y_2^{i-1}, K_{i+1}^n). \end{aligned}$$

Then set

$$(X_1,X_2,Y_1,Y_2,G,K,V_1,V_2,W_1,W_2,W_3,W_4) = (X_{1Q},X_{2Q},Y_{1Q},Y_{2Q},G_Q,K_Q,V_{1Q},V_{2Q},W_{1Q},W_{2Q},W_{3Q},W_{4Q}).$$

This joint distribution need not factorize as

$$p(q)p(x_1|q)p(x_2|q)p(w_1,v_1|x_1,x_2,q)p(w_2,v_2|x_1,x_2,q)p(w_3|x_1,x_2,q)p(w_4|x_1,x_2,q),$$

but this condition can be imposed (without loss of generality) because the expressions in the statement of the theorem depend only on the marginal distributions of (Q,X_1,X_2,V_1,W_1), (Q,X_1,X_2,V_2,W_2), (Q,X_1,X_2,W_3), and (Q,X_1,X_2,W_4).

3) Proof of the bound on R_1 in (4)*:* By Fano's inequality,

$$n(R_1-\delta_n) \le I(M_1;Y_1^n) \le I(X_1^n;Y_1^n),$$

where $\delta_n \to 0$ as $n\to\infty$. Using the independence of X_1^n and X_2^n, we write

$$\begin{aligned} n(R_1-\delta_n) &\le I(X_1^n;Y_1^n)\\ &\le I(X_1^n;Y_1^n|X_2^n)\\ &= I(X_1^n;Y_1^n|X_2^n) - I(X_1^n;G^n|X_2^n) + I(X_1^n;G^n|X_2^n). \end{aligned}$$

The difference $I(X_1^n;Y_1^n|X_2^n) - I(X_1^n;G^n|X_2^n)$ is handled by expanding over time and then applying the definitions of W_{3i}:

$$\begin{aligned} &I(X_1^n;Y_1^n|X_2^n) - I(X_1^n;G^n|X_2^n)\\ &= \sum_{i=1}^n \Big[I(X_1^n;Y_{1i}|X_2^n,Y_1^{i-1},G_{i+1}^n) - I(X_1^n;G_i|X_2^n,Y_1^{i-1},G_{i+1}^n)\Big]\\ &= \sum_{i=1}^n \Big[I(X_{1i};Y_{1i}|X_2^n,Y_1^{i-1},G_{i+1}^n) - I(X_{1i};G_i|X_2^n,Y_1^{i-1},G_{i+1}^n)\Big]\\ &= \sum_{i=1}^n \Big[I(X_{1i};Y_{1i}|X_{2i},W_{3i}) - I(X_{1i};G_i|X_{2i},W_{3i})\Big]. \end{aligned} \tag{15}$$

For the second part, note that by (1) the effective channel from X_1^n to G^n is memoryless and does not depend on X_2^n, so

$$I(X_1^n;G^n|X_2^n) = I(X_1^n;G^n).$$

By the Csiszár–Körner–Marton sum identity and the definition of W_{2i}, we obtain

$$\begin{aligned} I(X_1^n;G^n) &= \sum_{i=1}^n I(X_{1i};G_i|G^{i-1}) &(16)\\ &\le \sum_{i=1}^n I(X_{1i},Y_{2,i+1}^n;G_i|G^{i-1})\\ &= \sum_{i=1}^n I(X_{1i};G_i|G^{i-1},Y_{2,i+1}^n) + I(G^{i-1};Y_{2i}|Y_{2,i+1}^n) &(17)\\ &\le \sum_{i=1}^n I(X_{1i};G_i|G^{i-1},Y_{2,i+1}^n) + I(G^{i-1},Y_{2,i+1}^n;Y_{2i})\\ &= \sum_{i=1}^n \big[I(X_{1i};G_i|W_{2i}) + I(W_{2i};Y_{2i})\big]. \end{aligned}$$

Here, (16) uses the memorylessness from X_1^n to G^n, and (17) follows from the Csiszár–Körner–Marton sum identity.

Combining (15) and the last display, and then applying the time-sharing variable Q, yields

$$R_1 \le I(X_1;Y_1|X_2,W_3,Q) - I(X_1;G|X_2,W_3,Q) + I(X_1;G|W_2,Q) + I(W_2;Y_2|Q),$$

which is (4).

4) Proofs of the remaining bounds on R_1: For (5), we start from

$$n(R_1-\delta_n) \le I(X_1^n;Y_1^n|X_2^n) = \sum_{i=1}^n I(X_1^n;Y_{1i}|X_2^n,Y_{1,i+1}^n) \le \sum_{i=1}^n I(X_1^n,K^{i-1};Y_{1i}|X_2^n,Y_{1,i+1}^n).$$

Using the Markov chain

$$K^{i-1} \to (X_2^n, Y_{1,i+1}^n) \to Y_{1i},$$

which follows from

$$K^{i-1} \to X_2^{i-1} \to (X_2^n, X_{1,i}^n) \to Y_{1,i}^n$$

this yields

$$\begin{aligned} n(R_1-\delta_n) &\le \sum_{i=1}^n I(X_1^n,K^{i-1};Y_{1i}|X_2^n,Y_{1,i+1}^n) \\ &= \sum_{i=1}^n I(X_1^n;Y_{1i}|X_2^n,Y_{1,i+1}^n,K^{i-1}) \\ &= \sum_{i=1}^n I(X_{1i};Y_{1i}|X_{2i},K^{i-1},Y_{1,i+1}^n) \\ &= \sum_{i=1}^n I(X_{1i};Y_{1i}|X_{2i},W_{1i}), \end{aligned}$$

and after time sharing we obtain

$$R_1 \le I(X_1;Y_1|X_2,W_1,Q),$$

which is (5).

For (6), we exploit the fact that, by (1), $I(X_1^n;K^n)=0$. Starting again from Fano's inequality,

$$n(R_1-\delta_n) \le I(X_1^n;Y_1^n) = I(X_1^n;Y_1^n) - I(X_1^n;K^n).$$

We expand the difference over time and use the definitions of W_{1i}:

$$\begin{aligned} &I(X_1^n;Y_1^n) - I(X_1^n;K^n) \\ &= \sum_{i=1}^n \Big[I(X_1^n;Y_{1i}|K^{i-1},Y_{1,i+1}^n) - I(X_1^n;K_i|K^{i-1},Y_{1,i+1}^n) \Big] \\ &= \sum_{i=1}^n \Big[I(X_{1i};Y_{1i}|W_{1i}) - I(X_{1i};K_i|W_{1i}) \\ &\qquad + I(X_1^{n\setminus i};Y_{1i}|X_{1i},W_{1i}) - I(X_1^{n\setminus i};K_i|X_{1i},W_{1i}) \Big]. \end{aligned}$$

The last term in brackets is nonpositive. Observe that the less-noisy condition (2) implies $I(U;Y_1|X_1,V) \le I(U;K|X_1,V)$ for any $(U,V)\to(X_1,X_2)\to(Y_1,K)$. Setting $U=X_1^{n\setminus i}$ and $V=W_{1i}$ shows that the last term in brackets is nonpositive. Therefore,

$$I(X_1^n;Y_1^n) - I(X_1^n;K^n) \le \sum_{i=1}^n \Big[I(X_{1i};Y_{1i}|W_{1i}) - I(X_{1i};K_i|W_{1i}) \Big],$$

and time sharing gives

$$R_1 \le I(X_1;Y_1|W_1,Q) - I(X_1;K|W_1,Q),$$

which is (6).

For (7), we note that

$$n(R_1-\delta_n) \le I(X_1^n;Y_1^n) = \sum_{i=1}^n I(X_1^n;Y_{1i}|Y_{1,i+1}^n) \le \sum_{i=1}^n I(X_1^n,Y_{1,i+1}^n;Y_{1i}).$$

It is immediate that

$$I(X_1^n, Y_{1,i+1}^n; Y_{1i}) \le I(V_{1i}, W_{1i}, X_{1i}; Y_{1i}),$$

and hence, after time sharing,

$$R_1 \le I(V_1, W_1, X_1; Y_1|Q),$$

which is (7).

5) Bounds on R_2 and the sum-rate: The proofs of the bounds (8)–(11) for R_2 are entirely analogous to those for R_1, with the roles of users 1 and 2 interchanged and with (G, W_2) replaced by (K, W_1) wherever appropriate. They follow from Fano's inequality for user 2, the memoryless structure of the channel, the factorization (1), and the less-noisy condition (3).

For the sum-rate bound (12), we start from

$$\begin{aligned} n(R_1 + R_2 - \delta_n) \le\ & I(X_1^n, X_2^n; Y_2^n|K^n) - I(X_1^n; Y_2^n|X_2^n, K^n) + I(X_2^n; K^n) \\ & + I(X_1^n, X_2^n; Y_1^n|G^n) - I(X_2^n; Y_1^n|X_1^n, G^n) + I(X_1^n; G^n). \end{aligned}$$

Using the independence between (X_1^n, G^n) and (X_2^n, K^n) implied by (1), we obtain

$$\begin{aligned} n(R_1 + R_2 - \delta_n) \le\ & I(X_1^n, X_2^n; Y_2^n|K^n) - I(X_1^n; Y_2^n|X_2^n, K^n) + I(X_2^n; K^n|X_1^n, G^n) \\ & + I(X_1^n, X_2^n; Y_1^n|G^n) - I(X_2^n; Y_1^n|X_1^n, G^n) + I(X_1^n; G^n|X_2^n, K^n). \end{aligned}$$

Regroup terms as

$$\begin{aligned} n(R_1 + R_2 - \delta_n) =\ & I(X_1^n, X_2^n; Y_2^n|K^n) + I(X_1^n, X_2^n; Y_1^n|G^n) \\ & + \Big(I(X_2^n; K^n|X_1^n, G^n) - I(X_2^n; Y_1^n|X_1^n, G^n)\Big) \\ & + \Big(I(X_1^n; G^n|X_2^n, K^n) - I(X_1^n; Y_2^n|X_2^n, K^n)\Big). \end{aligned} \tag{18}$$

We then expand each term over time and use the definitions of $(V_{1i}, V_{2i}, W_{1i}, W_{2i})$, as well as the less-noisy conditions (2)–(3), exactly as in the single-user bounds. This yields

$$\begin{aligned} n(R_1 + R_2 - \delta_n) \le \sum_{i=1}^{n} \Big(& I(X_{1i}, X_{2i}; Y_{2i}|K_i) + I(X_{1i}, X_{2i}; Y_{1i}|G_i) \\ & + I(X_{2i}; K_i|V_{1i}, W_{1i}, X_{1i}, G_i) - I(X_{2i}; Y_{1i}|V_{1i}, W_{1i}, X_{1i}, G_i) \\ & + I(X_{1i}; G_i|V_{2i}, W_{2i}, X_{2i}, K_i) - I(X_{1i}; Y_{2i}|V_{2i}, W_{2i}, X_{2i}, K_i)\Big), \end{aligned}$$

and, after time sharing, this gives the desired single-letter sum-rate inequality (12).

6) Derivation of the constraints (13)–(14)*:* Finally, we justify the constraints (13)–(14). Since user 1 can reliably decode its own message, the information it obtains about X_1^n from its own output must dominate the information about X_1^n contained in the other receiver's output, up to an $o(n)$ term. Formally,

$$-n\delta_n' \le I(X_1^n; Y_1^n, X_2^n) - I(X_1^n; Y_2^n) = I(X_1^n; Y_1^n|X_2^n) - I(X_1^n; Y_2^n),$$

for some $\delta_n' \to 0$. Using (1), we can write

$$I(X_1^n; Y_1^n|X_2^n) - I(X_1^n; Y_2^n) = \big[I(X_1^n; Y_1^n|X_2^n) - I(X_1^n; G^n|X_2^n)\big] + \big[I(X_1^n; G^n) - I(X_1^n; Y_2^n)\big].$$

The first bracket is single-letterized exactly as in (15), while the second bracket is treated as in (16)–(17), except that now we compare $I(X_1^n; G^n)$ with $I(X_1^n; Y_2^n)$ instead of $I(X_1^n; G^n)$ alone. This leads to

$$\begin{aligned} I(X_1^n; G^n) - I(X_1^n; Y_2^n) &= \sum_i I(X_1^n; G_i|G^{i-1}, Y_{2,i+1}^n) - I(X_1^n; Y_{2i}|G^{i-1}, Y_{2,i+1}^n) \\ &= \sum_i I(X_{1i}; G_i|G^{i-1}, Y_{2,i+1}^n) - I(X_1^n; Y_{2i}|G^{i-1}, Y_{2,i+1}^n) \qquad (19) \\ &\le \sum_i I(X_{1i}; G_i|G^{i-1}, Y_{2,i+1}^n) - I(X_{1i}; Y_{2i}|G^{i-1}, Y_{2,i+1}^n) \\ &= \sum_i I(X_{1i}; G_i|W_{2i}) - I(X_{1i}; Y_{2i}|W_{2i}) \end{aligned}$$

where (19) holds because of (1). and hence, after time sharing,

$$I(X_1; Y_1|X_2, W_3, Q) - I(X_1; G|X_2, W_3, Q) + I(X_1; G|W_2, Q) - I(X_1; Y_2|W_2, Q) \ge 0,$$

which is (13). The constraint (14) for user 2 follows by symmetry, using the analogous inequality

$$I(X_2^n; Y_2^n | X_1^n) - I(X_2^n; Y_1^n) \gtrsim 0$$

and reversing the roles of (G, W_2) and (K, W_1).

This completes the proof of Theorem 5.

Remark 2. It is possible to obtain a relaxed version of the above bound that does not use W_3 and W_4 but still passes through the corner points and has the correct sum-rate value in the weak interference regime. Specifically, by weakening (4) to

$$R_1 \le I(X_1; Y_1 | G, X_2, Q) + I(X_1; G | W_2, Q) + I(W_2; Y_2 | Q)$$

and (8) to

$$R_2 \le I(X_2; Y_2 | K, X_1, Q) + I(X_2; K | W_1, Q) + I(W_1; Y_1 | Q),$$

and dropping the constraints (13)–(14), we arrive at a simpler but looser outer region that still recovers the Costa–Polyanskiy–Wu corner points and the sum-rate point in the Gaussian weak interference regime.

B. Relationship to earlier bounds

1) Comparison to Theorem 1: In this section we show that the constraints in Theorem 5 imply the bound in Theorem 1. For any $\lambda \ge 1$, combining (11) and (12) gives

$$\begin{aligned}
R_1 + \lambda R_2 \le\ & I(X_1, X_2; Y_1 | G, Q) + I(X_1, X_2; Y_2 | K, Q) \\
& + I(X_2; K | V_1, W_1, X_1, G, Q) - I(X_2; Y_1 | V_1, W_1, X_1, G, Q) \\
& + I(X_1; G | V_2, W_2, X_2, K, Q) - I(X_1; Y_2 | V_2, W_2, X_2, K, Q) \\
& + (\lambda - 1) I(V_2, W_2, X_2; Y_2 | Q) \\
\le\ & I(X_1, X_2; Y_1 | G, Q) + I(X_1, X_2; Y_2 | K, Q) \\
& + I(X_2; K | V_1, W_1, X_1, G, Q) - I(X_2; Y_1 | V_1, W_1, X_1, G, Q) \\
& + I(X_1; G | V_2, W_2, X_2, K, Q) - I(X_1; Y_2 | V_2, W_2, X_2, K, Q) \\
& + (\lambda - 1) I(V_2, W_2, X_2; Y_2, K | Q) \\
\overset{(a)}{=}\ & I(X_1, X_2; Y_1 | G, Q) + \lambda I(X_1, X_2; Y_2 | K, Q) \\
& + I(X_2; K | V_1, W_1, X_1, G, Q) - I(X_2; Y_1 | V_1, W_1, X_1, G, Q) \\
& + I(X_1; G | V_2, W_2, X_2, K, Q) - \lambda I(X_1; Y_2 | V_2, W_2, X_2, K, Q) \\
& + (\lambda - 1) I(X_1, X_2; K | Q) \\
=\ & I(X_1, X_2; Y_1, G | Q) + \lambda I(X_1, X_2; Y_2, K | Q) \\
& + I(X_2; K | V_1, W_1, X_1, G, Q) - I(X_2; Y_1 | V_1, W_1, X_1, G, Q) \\
& + I(X_1; G | V_2, W_2, X_2, K, Q) - \lambda I(X_1; Y_2 | V_2, W_2, X_2, K, Q) \\
& - I(X_1; G | Q) - I(X_2; K | Q) \\
=\ & I(X_1; Y_1, G | Q) + \lambda I(X_2; Y_2, K | Q) \\
& + I(X_2; K | V_1, W_1, X_1, G, Q) - I(X_2; Y_1 | V_1, W_1, X_1, G, Q) \\
& + I(X_2; Y_1 | X_1, G, Q) - I(X_2; K | X_1, G, Q) \\
& + I(X_1; G | V_2, W_2, X_2, K, Q) - \lambda I(X_1; Y_2 | V_2, W_2, X_2, K, Q) \\
& + I(X_1; Y_2 | X_2, K, Q) - I(X_1; G | X_2, K, Q) \\
\le\ & \Big(I(X_1; G, Y_1) + \lambda I(X_2; K, Y_2) \\
& + \mathcal{C}_{p(x_1)p(x_2)} [I(X_1; G | X_2, K) - \lambda I(X_1; Y_2 | X_2, K)] \\
& - (I(X_1; G | X_2, K) - \lambda I(X_1; Y_2 | X_2, K)) \\
& + \mathcal{C}_{p(x_1)p(x_2)} [I(X_2; K | X_1, G) - I(X_2; Y_1 | X_1, G)] \\
& - (I(X_2; K | X_1, G) - I(X_2; Y_1 | X_1, G)) \Big),
\end{aligned}$$

thus implying the bound in Theorem 1.

Here (a) uses the chain rule and the Markov property

$$(V_2, W_2, X_1) \to (X_2, Q) \to K,$$

which implies $I(V_2, W_2, X_1; K|X_2, Q) = 0$ and hence

$$I(V_2, W_2, X_2; K|Q) = I(X_2; K|Q).$$

More precisely,

$$\begin{aligned} I(V_2, W_2, X_2; Y_2, K|Q) &= I(V_2, W_2, X_2; K|Q) + I(V_2, W_2, X_2; Y_2|K, Q) \\ &= I(X_2; K|Q) + I(V_2, W_2, X_2; Y_2|K, Q) \\ &= I(X_1, X_2; K|Q) + I(X_1, X_2; Y_2|K, Q) - I(X_1; Y_2|V_2, W_2, X_2, K, Q). \end{aligned}$$

2) Comparison with Theorem 3: In this section we show that the constraints in Theorem 5 imply the outer bound stated in Theorem 3.

We specialize to the case where the given channel is a Z-interference channel and introduce an auxiliary receiver J satisfying

$$p_{J,Y_1,Y_2|X_1,X_2} = p_{J|X_1}\, p_{Y_2|J,X_2}\, p_{Y_1|J,X_1},$$

with J more-capable than Y_1.

In Theorem 5, we set $G = J$ and let K be constant. We first verify that these choices satisfy the less-noisy conditions. The first condition holds trivially because $I(U; Y_1|X_1) = 0$, and for the second we note that

$$I(V; J|X_2) = I(V; J, Y_2|X_2) \geq I(V; Y_2|X_2).$$

With these choices, the individual rate constraints reduce to

$$\begin{aligned} R_1 \leq\ & I(X_1; Y_1|X_2, W_3, Q) - I(X_1; J|X_2, W_3, Q) \\ & + I(X_1; J|W_2, Q) + I(W_2; Y_2|Q), \end{aligned} \tag{20}$$

$$R_1 \leq I(X_1; Y_1|X_2, W_1, Q), \tag{21}$$

$$R_1 \leq I(X_1; Y_1|W_1, Q), \tag{22}$$

$$R_1 \leq I(X_1; Y_1|Q), \tag{23}$$

and

$$\begin{aligned} R_2 \leq\ & I(X_2; Y_2|X_1, W_4, Q) \\ & + I(W_1; Y_1|Q), \end{aligned} \tag{24}$$

$$R_2 \leq I(X_2; Y_2|X_1, W_2, Q), \tag{25}$$

$$R_2 \leq I(X_2; Y_2|W_2, Q) - I(X_2; J|W_2, Q), \tag{26}$$

$$R_2 \leq I(V_2, W_2, X_2; Y_2|Q). \tag{27}$$

Since J is more-capable than Y_1, we have

$$I(X_1; Y_1|X_2, W_3, Q) - I(X_1; J|X_2, W_3, Q) \leq 0,$$

so the first term in (20) is nonpositive. It follows that the constraints (20), (23), (25), and (26) together imply all the rate bounds in Theorem 3.

Finally, the structural constraint (13) reduces to

$$\begin{aligned} & I(X_1; Y_1|X_2, W_3, Q) - I(X_1; J|X_2, W_3, Q) \\ & \quad + I(X_1; J|W_2, Q) - I(X_1; Y_2|W_2, Q) \geq 0. \end{aligned}$$

Using again that J is more-capable than Y_1, we have

$$I(X_1; Y_1|X_2, W_3, Q) \leq I(X_1; J|X_2, W_3, Q),$$

so the first line in the display is nonpositive. Hence (13) implies

$$I(X_1; J|W_2, Q) - I(X_1; Y_2|W_2, Q) \geq 0,$$

which is precisely the auxiliary constraint appearing in Theorem 3.

C. Application of the bound to the Gaussian interference channel

We now explain how the combined outer bound specializes to the scalar Gaussian interference channel and how it relates to the known slope discontinuities of its capacity region in the very weak interference regime.

In the very weak interference regime,

$$a(1+b^2P_2)+b(1+a^2P_1)<1,$$

it is known that:

- genie-aided outer bounds yield a tight characterization of the weighted sum-rate near the *sum-capacity point*, thereby revealing a slope discontinuity of the boundary of the capacity region at that point;
- auxiliary-receiver outer bounds for the corresponding Z-interference channels yield tight characterizations near each of the Costa–Polyanskiy–Wu (CPW) corner points, thereby revealing the two additional slope discontinuities at those corner points.

Our combined bound was designed specifically to subsume these two classes of bounds. At the level of general discrete memoryless interference channels, we showed:

1) for any choice of (G,K), the combined outer bound is contained in the genie-aided outer bound;
2) by specializing to Z-interference channels and choosing $G=J$ and K constant, the combined outer bound is no larger than the earlier auxiliary-receiver outer bound.

Therefore, when we restrict attention to the Gaussian channel and optimize over (G,K), our bound reduces exactly to the previously derived genie-aided and auxiliary-receiver bounds in the parameter ranges where each of them is known to be tight. In particular, for the Gaussian channel in the very weak interference regime:

- if we choose (G,K) so that the combined bound reproduces the genie-aided construction, then the resulting weighted sum-rate bound coincides with the known genie-aided expression near the maximum sum-rate point. Hence the combined bound exhibits the same slope discontinuity of the capacity boundary at the sum-capacity point.
- if we instead choose (G,K) in accordance with the earlier auxiliary-receiver construction for the Z-interference channel (and specialize to the appropriate one-sided Gaussian channel), then the combined bound reproduces the auxiliary-receiver outer region near each CPW corner point. Consequently, the combined bound exhibits the two slope discontinuities at the CPW corner points that arise in that construction.

1) On evaluation of the bound for Gaussian interference channels: A natural choice of auxiliary receivers is

$$\begin{aligned}
G &= X_1+\eta_1 Z_1^\dagger,\\
Y_1 &= X_1+bX_2+\rho_1 Z_1^\dagger+\sqrt{1-\rho_1^2}\,Z_1,\\
K &= X_2+\eta_2 Z_2^\dagger,\\
Y_2 &= X_2+aX_1+\rho_2 Z_2^\dagger+\sqrt{1-\rho_2^2}\,Z_2,
\end{aligned}$$

where $Z_1^\dagger, Z_1, Z_2^\dagger, Z_2$ are independent standard normal random variables .

For this choice of auxiliary receivers, the "doubling followed by rotation" trick [14] can be used to show that jointly Gaussian inputs are extremal. In particular, if $|\eta_1|\le 1$, then the choice $W_3=X_1$ maximizes the relevant mutual information terms, whereas if $|\eta_1|>1$, then the maximizing choice is to take W_3 to be constant. Similarly, if $|\eta_2|\le 1$, then $W_4=X_2$ is optimal, while if $|\eta_2|>1$, then it is optimal to take W_4 to be constant.

Furthermore, we may assume that the conditional covariance matrices do not depend on Q and are of the form

$$0\preceq K_{X_1X_2|W_1}=\begin{bmatrix} K_{11} & \omega_1\sqrt{K_{11}K_{21}}\\ \omega_1\sqrt{K_{11}K_{21}} & K_{21}\end{bmatrix}\preceq\begin{bmatrix}P_1&0\\0&P_2\end{bmatrix},$$

and

$$0\preceq K_{X_1X_2|W_2}=\begin{bmatrix} K_{12} & \omega_2\sqrt{K_{12}K_{22}}\\ \omega_2\sqrt{K_{12}K_{22}} & K_{22}\end{bmatrix}\preceq\begin{bmatrix}P_1&0\\0&P_2\end{bmatrix}.$$

Finally, we can impose

$$0\le K_{X_1|V_2,W_2,X_2}\le K_{12}(1-\omega_2^2)\quad\text{and}\quad 0\le K_{X_2|V_1,W_1,X_1}\le K_{21}(1-\omega_1^2).$$

The reader is referred to [9], [11] for related arguments that justify these structural assumptions on the maximizing distributions.

IV. Conclusion

We have presented a new outer bound for the discrete memoryless two-user interference channel that combines genie-aided and add-and-subtract techniques into a single unified framework. By introducing two auxiliary receivers (G, K) that satisfy a product structure and less-noisy-type conditions, we obtain a family of single-letter inequalities on (R_1, R_2) parameterized by auxiliary random variables. In the Gaussian interference channel with weak interference, appropriate specialization of these auxiliaries yields an outer region that passes through the Costa–Polyanskiy–Wu corner points and the maximum sum-rate point, and exhibits all three corresponding slope discontinuities of the true capacity region.

Beyond reproducing the best-known sum-capacity and corner-point characterizations as special cases, the proposed bound clarifies how genie-based and add-and-subtract arguments can be blended systematically.

References

[1] A. El Gamal and Y.-H. Kim, *Network Information Theory*. Cambridge University Press, 2012.

[2] H. Sato, "An outer bound to the capacity region of broadcast channels," *IEEE Trans. Info. Theory*, vol. IT-24, pp. 374–377, May, 1978.

[3] M. H. M. Costa and A. El Gamal, "The capacity region of the discrete memoryless interference channel with strong interference (corresp.)," *Information Theory, IEEE Transactions on*, vol. 33, no. 5, pp. 710–711, 1987.

[4] V. Annapureddy and V. Veeravalli, "Gaussian interference networks: Sum capacity in the low-interference regime and new outer bounds on the capacity region," *Information Theory, IEEE Transactions on*, vol. 55, no. 7, pp. 3032–3050, july 2009.

[5] A. Motahari and A. Khandani, "Capacity bounds for the Gaussian interference channel," *Information Theory, IEEE Transactions on*, vol. 55, no. 2, pp. 620–643, feb. 2009.

[6] X. Shang, G. Kramer, and B. Chen, "A new outer bound and the noisy-interference sum-rate capacity for Gaussian interference channels," *Information Theory, IEEE Transactions on*, vol. 55, no. 2, pp. 689–699, feb. 2009.

[7] S. Liu, "Genie-based outer bounds for interference channels," Ph.D. dissertation, The Chinese University of Hong Kong, 2016.

[8] W. H. Ng, "On gaussian extremizers for the capacity region of the gaussian interference channel," Ph.D. dissertation, The Chinese University of Hong Kong, 2021.

[9] A. El Gamal, A. Gohari, and C. Nair, "A strengthened cutset upper bound on the capacity of the relay channel and applications," *IEEE Transactions on Information Theory*, 2022.

[10] A. Gohari, C. Nair, and J. Zhao, "On the capacity region of some classes of interference channels," in *2024 IEEE International Symposium on Information Theory (ISIT)*, 2024, pp. 3136–3141.

[11] A. Gohari and C. Nair, "Outer bounds for multiuser settings: The auxiliary receiver approach," *IEEE Transactions on Information Theory*, vol. 68, no. 2, pp. 701–736, 2022.

[12] Z. Wen and A. Gohari, "A new upper bound for distributed hypothesis testing using the auxiliary receiver approach," *arXiv preprint arXiv:2409.14148*, 2024.

[13] Z. Chen, A. Gohari, and C. Nair, "A differential equation approach to the most-informative boolean function conjecture," *arXiv preprint arXiv:2502.10019*, 2025.

[14] Y. Geng and C. Nair, "The capacity region of the two-receiver Gaussian vector broadcast channel with private and common messages," *IEEE Transactions on Information Theory*, vol. 60, no. 4, pp. 2087–2104, April 2014.